



Datasheet
186-4623
RSPRO-F13R



USB Rechargeable Pocket Tool-Light

 **600**
LUMENS



Magnet
On Base



4 Light
Settings



USB Charging
Cable Inc.



Technical Data

600 Lumen White LED
Multi-functional strong aluminium Tool-piece
Tough aircraft-grade aluminium construction
Super strong magnetic base
Built in USB rubberised charging point
Flawless smooth reflector for long distance beam
SOS and Strobe functions
IPX4 water resistant

Product Size: 94.5 x 26.5 mm




Product Weight: 110g

Battery: Rechargeable built-in 3.7v 700mAh Li-polymer

Charger: Micro-USB cable (Included)

Charging time: approx 3 hours

LED charging indicator: Red-Charging, Green-Fully charged

MODE			
HIGH	600 lm	120 m	50mins
LOW	165 lm	65 m	110mins
STROBE	--	--	60mins
SOS	--	--	80mins

Operation

High > Low > Strobe > SOS > Off

ADVICE & IMPORTANT INFORMATION!

- Do not look directly at the LED.
- Do not operate in direct sunlight or extreme temperature conditions (below -10°C or above 40°C).
- The LED will become hot when switched on; do not touch and do not place face down on any surface – risk of fire!
- Do not use the device if there is any visible damage to the housing or cable.
- The aluminium housing can get warm. If it gets too hot turn down the brightness or turn off and allow to cool.
- Do not use the lamp in the immediate vicinity of flammable materials or gases.
- Children under 12 years of age should only use the product under adult supervision.
- Before cleaning the product, disconnect the charge cable. Clean with a dry or slightly moist, clean, lint-free cloth and a mild detergent if required. Do not use cleaners that contain abrasives or solvents.
- Do not open, disassemble or attempt to modify the product; this will void the warranty and can be dangerous.
- Improper use or modification is not covered under the warranty.
- Ensure the lens does not come into contact with hard/sharp objects; damage to the lens may affect light output.
- To maintain rechargeable batteries, distributors should recharge the battery every 6 months and users should recharge every 3 months if not using for an extended period.
- Fully charge the product before storage.
- The rechargeable battery will reach optimum performance only after several complete charging and discharging cycles.
- Protect the battery from heat, intense sunlight, fire, water and moisture – danger of explosion!
- If the battery is damaged, fluids can leak out. AVOID contact as this can lead to skin irritation and/or burns. If skin contact happens, rinse thoroughly with water. If irritation persists, seek medical advice. Also seek immediate medical assistance if battery fluid comes into contact with the eyes.
- Do not dispose of this device in normal household waste. It must be disposed of via an authorised disposal centre or at your local waste disposal unit.
- Please recycle packaging where possible.
- Keep these instructions for future reference or for subsequent possessors.

